

PowerMate 1000 (1000VA) AVR, Schuko



PM 1000 AVR



PM 1000 AVR Top side

Features

- Compact size with robust design
- Very wide input voltage range
- Excellent output voltage stability
- Extremely fast response
- Provides over voltage & under voltage short circuit and temperature protection

MODEL		PowerMate 1000 (1000VA) AVR, Schuko
INPUT		
Voltage Range	Capacity	1000VA/600W
	Input Voltage	183-285VAC
	Phase	Single
	Input Frequency	50 Hz (auto sensing)
	Voltage regulation	220V +6% /- 10%
	Output AVR	Same as input
INDICATOR		
LED green		Normal mode
LED Red		Over Voltage, Overload
LED Yellow		AC AVR Mode
PROTECTION		
Comprehensive Protection		Short circuit, overload and over-temperature protection
PHYSICAL		
Dimension, L X W X H (mm)		180 x 95 x 119 (mm)
Net Weight (kgs)		1,6
Outlets		3 Schuko
ENVIRONMENT		
Humidity		0-90% RH @ 0-40° C (non-condensing)
Noise Level		Less than 40 dB