■ General Specifications

Description		ScanSnap iX100		
Scanner type		CDF (Continuous Document Feeding), Simplex sheetfeed two-way paper path (Straight path, U-turn path)		
Scanning modes	S	Color, grayscale, monochrome, automatic (color / grayscale / monochrome detection)		
Image sensor		CIS (Contact Image Sensor) x 1		
Light source		3 Color LED (Red / Green / Blue)		
Optical resolution	n	600 dpi		
Auto mode (default) *2 Normal mode (150 dpi)		5.2 seconds / page		
speed *1 (A4 portrait)	Better mode (200 dpi) Best mode (300 dpi)			
	Excellent mode (600 dpi)	20.4 seconds / page		
Degument dies	Normal mode	A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 25.4 x 25.4 mm (1 x 1 in.)) / Automatically recognizes document size		
Document size	Normal mode with Carrier sheet	Use of a carrier sheet permits the scanning of A3, B4, double letter and photographs as well as the document sizes that are listed above.		
	Long paper scanning *4	Max: 216 x 863 mm (8.5 x 34 in.) (300 dpi or less)		
Paper weight (Thickness)		52.3 to 209.3 g/m², or 14 to 56 lb (Straight path) 52.3 to 80 g/m², or 14 to 20 lb (U-turn path) Card Portrait or Landscape (Straight path) Non-embossed: 0.76 mm or less Embossed: 0.76 + 0.48 mm (ISO7810 Conforming)		
Paper setting		Front side up		
Continuous scanning		260 sheets (A4, color, simplex, 300 dpi, battery operated)*5		
Interface *6		USB 2.0 (USB 1.1 compatible)		
Power source		Li-ion Batterry (3.7 V / 720 mAh)		
Power requirement		5 V / 0.5 A (x 1port)		
Power consumption *7		During operation: 4.7 W or less During sleep mode: 2.2 W or less During Auto Standby (OFF) mode: Less than 0.5 V		
Operation environment		Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80% (Non-condensing)		
Dimensions (W x D x H)*8		273 x 47.5 x 36 mm (10.74 x 1.87 x 1.42 in.)		
Device weight		400 g (0.88 lb)		
Environmental c	ompliance	ENERGY STAR® / RoHS		
Multifeed detect	ion	None		
Driver		ScanSnap specific driver Windows®: Does not support TWAIN / ISIS™ Mac OS: Does not support TWAIN		

lolided A3, 64 of Double letter size document one slide at a limit. The limitage is automatically stitled only in texts or diagrams cover across the two-page spread. *4 The IXIO is capable of scanning documents that exceed A4 size in length. This function is available for all modes except for "Excellent mode". *5 The number of sheets that can be scanned when connected to a computer via Wi-Fi with fully charged battery. The number of sheets may vary due to the system environment used, usage method and repeated charging. *5 Computer with USB 3.0 will work as USB 2.0 year and the control only with USB cable provided with product. *7 When operating with battery. *8 When other is closed.

■ Software

	Windows®	Mac OS		
Driver *1	ScanSnap Manager	ScanSnap Manager		
	ScanSnap Organizer	ScanSnap Organizer		
	ScanSnap Receipt	ScanSnap Receipt		
Applications	CardMinder	CardMinder		
	ABBYY FineReader for ScanSnap™	ABBYY FineReader for ScanSnap™		
	Scan to Microsoft SharePoint	-		

^{*1} TWAIN or ISIS™ applications cannot be used directly.

■ Included items

●Getting started ●Set-up DVD-ROM ●USB cable

■ Consumables

Cleaner F1 PA03950-0352 100 ml bottle Used to clean rollers Cleaning Wine PA03950-0419 1 pack (24 packets)	Description	Part number	Remarks
Olassias Wiss Dagges and 1 pack (24 packets)	Cleaner F1	PA03950-0352	100 ml bottle Used to clean rollers
Used to clean rollers	Ol		1 manual (O4 manulanta)

■ ScanSnap iX100 System Requirements

Recommended operating systems		Windows® 10 (32-bit / 64-bit) *1	Windows® 8.1 (32-bit / 64-bit) *1	Windows® 7 (32-bit / 64-bit)		
	ScanSnap Manager	Supported	Supported	Supported		
	ScanSnap Organizer	Supported	Supported	Supported		
Driver /	ScanSnap Receipt *3	Supported	Supported	Supported*4		
Applications *2	CardMinder*3	Supported	Supported	Supported		
	ABBYY FineReader for ScanSnap™	Supported	Supported	Supported		
	Scan to Microsoft SharePoint	Supported	Supported	Supported		
	CPU*6	Intel® Core™ i5 2.5 GHz or higher				
Hardware requirements	Memory capacity*6	4 GB or more				
	Display	1,024 x 768 pixels or higher		800 x 600 pixels or higher		
	Disk capacity *7	3.5 GB or	disk space			
	DVD-ROM drive	Red	N*8			
	USB port *6 *9	USB 3	ISB 1.1			

Mac OS

Muooo							
Recommended operating systems		macOS v10.12 (Recommended: v10.12.1or later)*2	OS X v10.11	OS X v10.10	OS X v10.9 (Recommended: v10.9.5 or later)	OS X v10.8 (Recommended: v10.8.5 or later)	Mac OS X v10.3 (Recommended v10.7.5 or later)
	ScanSnap Manager	Supported	Supported	Supported	Supported	Supported	Supported
Driver / Applications *1	ScanSnap Organizer	Supported	Supported	Supported	Supported	Supported	Supported
	ScanSnap Receipt *2	Supported	Supported	Supported	Supported	Supported	Supported
	CardMinder	Supported	Supported	Supported	Supported	Supported	Supported
	ABBYY FineReader for ScanSnap™*3	Supported	Supported	Supported	Supported	Supported	Supported
	CPU*5	Intel® Core™ i5 2.5 GHz or higher					
Hardware requirements *4	Memory capacity *5	4 GB or more					
	Display	1,024 x 768 pixels or higher					
	Disk capacity	2.5 GB or more of free hard disk space					
	DVD-ROM drive	Required for installation *6					
	USB port *5 *7	USB 3.0 *8 / USB 2.0 / USB 1.1					
1 Please refer to the ScanSnap website for the latest support information, *2 Please visit the website of				hsite of th			

** I Hease reter to the ScanSnap website for the latest support information. **2 Please visit the website of the company for download information. (http://scansnap.fujitsu.com/g-support/en/) *3 Compatibility may differ depending on the software's version. *4 The ScanSnap device may not work if the connected computer does not meet these requirements. *5 Scanning speeds may drop if recommended CPU, memory capity and USB 1.1 requirements are not met. *6 if you have no DVD-ROM drive, please visit the website of the company. (http://scansnap.fujitsu.com/g-support/en/) *7 ScanSnap operates on both USB 2.0 and USB 3.0 without any difference in performance. *8 Some computers do not recognize the ScanSnap when it is connected to a USB 3.0 port. In this case, please use a USB 2.0 port. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

Options

Description Part number		Remarks		
	PA03010-6571 USA, Canada & Taiwan			
	PA03010-6581 EMEA, England			
	PA03010-6591 China	The AO adeata are also as the second		
AC adapter	PA03010-6601 Korea	The AC adapter may vary depending on the country where you purchased the ScanSnap and the specifications of the ScanSnap.		
	PA03010-6611 Australia	specifications of the octationary.		
	PA03010-6621 India			
	PA03010-6631 Brazil			
ScanSnap iX100 Case *1	PA03688-0001			
ScanSnap iX100 Soft Case *1	PA03688-0011	Intended for ScanSnap iX100		
ScanSnap Carrier Sheets *2	PA03360-0013	5 Carrier Sheets Intended for ScanSnap iX500, iX100, S1500, S1500M, S1100i, S1100		

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some jurisdictions. ABBYY™ FineReader™ Engine ©ABBYY ABBYY *Evernote is a registered trademark or trademark of registered in Sorile jurisoilizonis. ABBYY *Furnote is a registered trademark or trademark of Evernote Corporation. *Google and Google Drive are registered trademarks or trademarks or sold in the Corporation in the United States and other countries. *Miscs* is a registered trademark of EMC Corporation in the United States. *Mac, Mac OS, Mac logo and iPhoto are trademarks of Apple Inc. *Microsoft, Windows, Windows Vista, Excel, PowerPoint, SharePoint, Internet Explorer and OneDrive are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. *Word is the products of Microsoft Corporation in the United States. *PowerPo is a registered trademarks or trademark of the States and/or other countries. *Word is the products of Microsoft Corporation in the United States. *PowerPo is a registered trademarks or trademark of the States and/or other countries, or both. *Salesforce and Salesforce CRM are registered trademarks or trademarks of salesforce.com, inc. in the United States and other countries. *ScanSnap, ScanSnap logo, ScanSnap Manager, ScanSnap Organizer and CardMinder are registered trademarks or trademarks of PFU Limited in Japan. *Other company names and product names are the trademarks or registered trademarks of the respective companies.





For more ScanSnap related information, visit our website at : http://scansnap.fujitsu.com/

↑ Safety Precautions Be sure to carefully read all safety precautions prior to using this product and use this device as instructed.

Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product.

©2017 PFU Limited Printed in some country 2017.4 U-155 AMN-50K3





WSB 3.0 *10 VSB 2.0 V USB 1.1

*10 Please visit the velsite of the company for download information. (http://scansnap.fujitsu.com/g-support/en/) *4

Please visit the velsite of the company for download information. (http://scansnap.fujitsu.com/g-support/en/) *4

Requires Service Pack 1. *5 The Scansnap device may not work if the connected computer does not meet these requirements. *6 Scanning speeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *₹7 Microsoft. NET Frimework 3.5 SP1 will be installed (Peuines 500 MB of disk space) logether with ScanSnap Manager, ScanSnap Organizer or CardMinder for systems that do not have .NET Framework 3.5 SP1 installed. When using "Scan to Google Drive" with ScanSnap Manager/ScanSnap Organizer, users also need to install either. .NET Framework 4 or in-place updates of .NET Framework 4. *8 If you have no DVD-ROM drive, please visit the website of the company. (http://scansnap.fujitsu.com/g-support/en/) *9 ScanSnap operates on both USB 2.0 and USB 3.0 ond USB 3.0 ond

ScanSnap

iX100

Simple, Speedy & Compact. From Paper to PDF in One Touch!



- ▶ The fastest mobile scanner in its class
- ▶ Built-in Wi-Fi Automatically switches the connection modes between Access Point Connect Mode and Direct Connect mode
- ▶ Battery operated, no need for cable connection
- ▶ Various functions for making your daily work

Software

shaping tomorrow with you

- ► ScanSnap Receipt (Win / Mac)
- CardMinder (Win / Mac)

Specifications are subject to change without notice.



Productivity unleashed

The world's lightest compact body*

The iX100 is only 400g in weight even with built-in battery and Wi-Fi connectivity. The compact and light body make it a convenient companion when traveling or on the road.

*Based on the investigation by PFU Limited on A4 document feed type scanner with built-in battery and Wi-Fi connectivity. (as of March 1st, 2017)

The fastest mobile scanner in its class*

The iX100 is the fastest A4 sheetfeed scanner with built-in battery and Wi-Fi connectivity; it can scan at a snappy speed of 5.2 seconds/page for color A4 document at a resolution of up to 300 dpi.

*Based on the investigation by PFU Limited on A4 document feed type scanner with built-in battery and Wi-Fi connectivity. (as of March 1st, 2017)

Battery operated, no need for cable connection

The iX100 can be scanned without the cables, so you can use it when power supply is unavailable or limited. The scanner is always ready to be used immediately when needed.

Scans plastic cards and other various document types*

In addition to standard paper types, the iX100 can scan plastic cards like the ones used for membership IDs.





Continuous Document Feeding (CDF Function)

The Continuous Document Feeding function allows you to insert pages one after another without pressing any extra button by detecting when a sheet enters and exits the iX100.

Two selectable paper paths

Switch iX100's output guide to either the folded position for the straight

path or the open position for the U-turn path to best suit the document you want to scan.


Straight path

Most suitable for scanning post cards, photos, business cards, plastic cards*, ScanSnap Carrier Sheet (Option), and common office paper.

*This applies to standard ISO 7810 ID-1 card types.

●U-turn path

Most suitable for scanning common office paper and you do not need extra space for the document output.



Feed guide

Quick Menu saves time

Even first-time ScanSnap user can master the functions by navigating through the Quick Menu. ScanSnap's Quick Menu automatically pops up after scanning to enable you to link the data to an application, quickly and easily. You do not have to remember any complicated procedures; just simply click the icon on screen.

Quick Menu: Favorites (Windows®)



It can be easily customized to display just your favorites.

Quick Menu:Recommended (Windows®)



Icons of the recommended application is displayed in priority.

•Scanning a two-sided document using the CDF Function



Set a page of your document face-up into the iX100 and push the Scan button to start the scanning.



The iX100 proceeds to scan the front side of that page.

The page exits from the top of the scanner which has its paper path set to the U-turn



Simply reinsert the same page (which exits face-down) without pressing the Scan button to smoothly scan the other side.



After you finish scanning your document, press the Scan button again to end the scanning and convert the data to a PDF image file

Easily links documents to clouds

You can scan nearly effortlessly to Evernote, Google Drive, Salesforce, SugarSync and Dropbox, and then conveniently browse the data from computers, tablets or smartphones - anywhere, anytime.

●ScanSnap Folder [Windows®]

Scan to virtually any application or web service that can open, insertor attach a PDF or JPEG file from your Windows computer. In this way, you do not have to save the data in the computer beforehand.



No need to switch the Wi-Fi mode manually for comfortable scanning anywhere, anytime more convenient

The ScanSnap iX100 is equipped with built-in Wi-Fi which is able to

automatically detect and switch to the network environment at

home, in the office or on the go. You only need to set up initially and

iX100 can be scanned wirelessly directly to any platform even

•In the office: Connect to the secured Wi-Fi network via IEEE802.1X

On the road: Connect via Direct Connect mode (do not need an

2 In the office

Access Point

(IEEE802.1X

Features for quick digitization

authentication)

•Dual scan - scanning 2 small sized documents at the same time

Even documents larger than A4 size can be scanned without any

extra effort. Just fold the large documents in half and the iX100 will

automatically stitch the diagram or chart that is spread across two

The iX100 features a powerful set of automated image processing

functions including Auto deskew, Auto orientation, and Auto color

detection. These functions make pre-scan work like sorting pages

and changing scan settings unnecessary, so you can scan your

3 On the road

Direct Connect

mode

•At home: Connect via the access point of the router at home

without Wi-Fi network in the environment.

(network device authentication)

Access Point

Connect mode

You can scan 2 small sized documents

such as business card and receipt

at the same time. Simply insert

documents continuously to the

paper feeding entry to greatly

reduce your scanning time and

Automated features

documents with minimal effort.

Automatically stitch a two-page spread

for near effortless scanning

lead to increased efficiency.

pages after scanning.

access point)

With ScanSnap Sync, whichever device you are on, you can use scanned data from either ScanSnap Organizer or the mobile app ScanSnap Connect Application. ScanSnap Sync automatically synchronizes scanned data between the two. This gives you more flexibility for data management regardless of your location.

*ScanSnap Sync is realized by utilizing a third party cloud service such as Google Drive, OneDrive and Dropbox. For the latest support information of cloud services, please visit the ScanSnap website.

Efficiently organizes business card data

Business card organizer software

CardMinder [Windows® / Mac OS]

- •Scan your collection of business cards into easy to navigate digital business card holders.
- •Import the data from your scanned business cards into Excel, Outlook, Address book (Contacts: OS X v10.8 or later) and other database programs for fast referencing and application.

Generates Microsoft® Word, Excel®, PowerPoint® files

Top-class OCR engine

ABBYY FineReader for ScanSnap™ [Windows® / Mac OS]

Smoothly scan and convert paper documents into Word, Excel® and PowerPoint® documents.

*Only Microsoft® Word and Excel® are available for Mac OS.

*Only Microsoft® Word and Excel® are available for Mac C *Generated images and text may vary from the original.

Receipt software with multi-currency support

A few simple steps to digitize and manage the information on your receipts

ScanSnap Receipt allows you to easily scan and extract information from your receipts, and export the data for other accounting software. The sophisticated features within ScanSnap Receipt automatically support various languages and currencies.

*Please visit the ScanSnap website for details on which languages and currencies are supported.

Carrying case (Option)

Two convenient carrying cases intended for the iX100 are available. (See disclaimer under "Option" in the next page.)

